


## Clock Generator

Part No.	W83115RG-965
Datasheet	 <a href="#">Request PDF</a>
Description	<p>The W83115RG-965 is a CK505 Clock Synthesizer for Intel<sup>®</sup> chipsets. The W83115RG-965 provides all clocks required for the high-speed microprocessor and provides step-less frequency programming and 32 different frequencies of CPU, PCI, and SRC clocks setting. The W83115RG-965 also supports SATA and DOT clock outputs. All clocks are externally selectable with smooth transitions.</p> <p>The W83115RG-965 provides I2C serial bus interface to program the registers to enable or disable each clock output and provides -0.5% down type spread spectrum or programmable S.S.T. scale to reduce EMI.</p> <p>The W83115RG-965 accepts a 14.318 MHz reference crystal as its input and runs on a 3.3V supply.</p>
Features	<ul style="list-style-type: none"> <li>› 2 pairs of push-pull Differential clock outputs for CPU, 1 free running.</li> <li>› 7 pairs of push-pull Differential clock outputs for SRC.</li> <li>› 1 pair push-pull Differential clock outputs for CPU/SRC.</li> <li>› 1 pair push-pull Differential clock outputs for DOT/SRC.</li> <li>› 5 PCI clock outputs, 1 free running.</li> <li>› 1 48 MHz clock output for USB.</li> <li>› 1 14.318MHz REF clock output.</li> <li>› Smooth frequency switch with selections from 100 to 400MHz.</li> <li>› Step-less frequency programming, and programmable S.S.T. scale to reduce EMI in M/N mode.</li> <li>› I2C 2-wire serial interface and support byte read/write and block read/write.</li> <li>› -0.5% down type spread spectrum in H/W and software select mode.</li> <li>› Programmable registers to enable/disable each output and select mode.</li> <li>› Programmable clock output slew rate control and skew control.</li> </ul>
Diagram	N/A
Package	SSOP56
Other Files	N/A
Development Tools	N/A
Others	N/A

Contact us: [ComputerIC@nuvoton.com](mailto:ComputerIC@nuvoton.com)

